

VICTOR[®]
DIGITAL MULTIMETER
VICTOR-9205F



Maximum display	1999 (3 1/2 bits)	
Power supply	9V battery	
DC mV	200mV	$\pm (1.0\%+5)$
DCV	200.0mV/2.000V/20.00V/200.0V	$\pm (1.0\%+2)$
	1000V	$\pm (1.2\%+10)$
AC mV	200mV	$\pm (1.0\%+8)$
ACV	2.000V/20.00V/200.0V	$\pm(1.2\%+2)$
	750V	$\pm(1.4\%+10)$
DCA	200.0uA/2000uA/20.00mA/200.0mA	$\pm(1.2\%+3)$
	2A/10A	$\pm(1.5\%+10)$
ACA	200.0uA/2000uA/20.00mA/200.0mA	$\pm(2.0\%+15)$
	2A / 10A	$\pm(3.5\%+15)$
Resistance	200.0Ω/2.000kΩ/20.00kΩ/200.0kΩ	$\pm(1.0\%+25)$
	2.000MΩ/20.00MΩ	
Capacitance	20.00nF/200.0nF/2.000uF/20.00uF/200.0uF	$\pm(2.5\%+20)$
Frequency	20.00Hz/200.0Hz/2.000kHz/20.00kHz/200.0kHz	$\pm(0.5\%+10)$
Diode forward voltage drop	Test current: approximately 1mA Open circuit voltage: approximately 2.5V	
The buzzer sound at resistance less than (50 ±20)Ω	Test current: about 0.28mA	
hFE NPN or PNP	0 - 1000	
Overload protection	250V AC/DC	