

## Features

- Voltage detection from 90 to 1000 V ac, suitable for a wide range of residential, commercial and industrial needs.
- NEW! Always on, using special low power circuitry to sustain battery life and ensure your 2AC is always ready.
- NEW! Innovative 'Battery Check' button function ensures battery is in good condition\*
- Category IV - 1000 V overvoltage rated product for best in class user protection
- Integrated clip design, optimized for pocket storage
- Powered by 2x AAA batteries (included)
- Fluke ruggedness and reliability
- Two-year warranty

\*Use of Battery Check function is optional and for convenience only, it is not intended as a substitute for checking the unit on a known live source before and after use.



## Specifications

Specifications	
<b>Operating principle</b>	Senses the steady state electrostatic field produced by ac voltage through insulation without requiring contact to the bare conductor. A red glow at the tip indicates the presence of voltage.
<b>Safety Compliance:</b>	Meets IEC 61010-1:2001, UL 61010-1 (2nd ed.), CAN/CSA-C22.2 No. 61010-1-04, and ISA-82.02.01 Pollution Degree 2
<b>EMC Compliance:</b>	Meets IEC 61326-1:2006
<b>Operating:</b>	90 V ac to 1000 V ac, CAT IV 1000 V rated
<b>Temperature:</b>	Operating: -10 °C to 50 °C (-14 °F to 122 °F) Storage: -10 °C to 50 °C (-14 °F to 122 °F)
<b>Humidity:</b>	0 % to 95 % (0 °C to 30 °C) 0 % to 75 % (30 °C to 40 °C) 0 % to 45 % (40 to 55 °C)
<b>Altitude:</b>	2000 m (CAT IV 1000 V)
<b>Cleaning:</b>	Clean with damp cloth
<b>Battery Life</b>	Typical battery life of greater than one year
<b>Warranty Period:</b>	Two years
<b>FLK2AC/90-1000V</b>	Fluke 2AC VoltAlert™ Voltage Detector. 90-1000V, straight tip for North American style outlets.
<b>FLK2AC/90-1000V5PK</b>	Fluke 2AC VoltAlert™ Voltage Detector 5-pack. 90-1000V, straight tip for North American style outlets.