

VICTOR 6050



Basic functions	Range.	Basic accuracy
DC voltage	400mV/4V/40V/400V	$\pm(0.5\%+4)$
DC Current	400A 2000A	$\pm(2.5\%+20)$ $\pm(3.5\%+20)$
Diode test		√
Continuity Buzzer		√
Low Voltage Display		√
Auto power off		√
Hold		Data Hold
Automatic shutdown		√
Overload		√
Impedance		10MΩ
Sampling frequency		3 time/s
AC Current Frequency		(40-400)Hz
Mode of operation		Manual Range
Maximum display		3999
Jaw open		55mm
Power		9V